

1080nm PM Filter Coupler

FEATURES

- Low Excess Loss
- Various Splitting Ratio
- Wide Passband
- High Stability and Reliability
- Epoxy Free Optical Path

APPLICATIONS

- Optical Amplifier
- Optical Networks
- **Power Monitoring**
- Fiber Sensor
- Lab



SPECIFICATIONS

Parameter	Unit		1x2 Type	е	2x2 Type				
Center Wavel	nm	1080							
Bandwidth	nm	+/-15nm or customer specify							
Split Ratio		-	0.1:99.9	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio		-	0.1%	1+/-0.5%	2+/-0.6%	5+/-1.0%	10%	40%	50%
Excess Loss	Max.	dB		1.0		1.4			
Uniformity	Max.	dB		0.6		0.8			
Extinction Rat	tio	dB	2			≥20			
Optical Return	dB	≥50							
	Tap Port	-	Same Fiber, Corr. SM Fiber or 105/125um Fiber						
Fiber Type			PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L)						
	Thru Port	-	10/125um PMDC Fiber (O) or 15/130um PMDC Fiber (W)						
			20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)						
Work Mode Standard		-	Can only work in Slow Axis						
Work Mode	В Туре	-		Can work	both in S	low Axis and Fast Axis			
Fiber Tensile I	Fiber Tensile Load N 5								
Max. Optical F	mW	300							
Operating Ter	°C	0~50							
Storage Temperature		°C	-40~85						
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35						
Dimension	Metal Box	mm	(L)120x(W)12x(H)10						

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FPFC-NNNN	- NN	С	N	(C)	- (<mark>C</mark>)	С	С	NN	- CC/CCC
Wavelength	Split Ratio	Tap Port Fiber	Туре	Work Mode	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1080-1080nm	01-1/99	P=Same Fiber	<mark>1</mark> -1x2	B=B Type	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N-Without Connector
	<mark>05=</mark> 5/95	S=Corr. SM Fiber	<mark>2=2</mark> x2	<i>Blank</i> for Standard	<i>Blank</i> for SST	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	10-10/90	A= 105/125um Fiber				Q= 20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	50 =50/50					R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector







^{2.} To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.