

980nm High Power PM Filter Coupler

FEATURES

- Low Excess Loss
- Various Splitting Ratio
- Wide Passband
- High Stability and Reliability
- Epoxy Free Optical Path

APPLICATIONS

- Optical Amplifier
- Optical Networks
- Power Monitoring
- Fiber Sensor
- Lab



SPECIFICATIONS

Parameter		Unit	1x2 Type			2x2 Type			
Center Wavelength		nm	980						
Bandwidth		nm	+/-15						
Split Ratio		-	0.1:99.9	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio		-	0.1%	1+/-0.5%	2+/-0.6%	5+/-1.0%	10%	40%	50%
Excess Loss	Max.	dB	1.2			1.4			
Uniformity	Max.	dB	0.8			1.0			
Extinction Ratio		dB	≥ 18						
Optical Return Loss		dB	≥ 50						
Fiber Type	Tap Port	-	Same Fiber, Corresponding SM Fiber or 50/125um Fiber						
	Thru Port	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)						
Work Mode	Standard	-	Can only work in Slow Axis						
	B Type	-	Can work both in Slow Axis and Fast Axis						
Fiber Tensile Load		N	5						
Max. Optical Power (CW)		W	1, 2, 3, 5, 10						
Operating Temperature		°C	0~50						
Storage Temperature		°C	-40~85						
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35 (≤5W); (Ø)6.0x48 (5~10W)						
Dimension	Metal Box	mm	(L)90x(W)12x(H)10 (>10W); (L)120x(W)12x(H)10 (≤10W)						

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FPFC-NNN	-NN	C	N	(C)	-HP	NN	-(C)	C	C	NN	-CC/CCC
Wavelength	Split Ratio	Tap Port Fiber	Type	Work Mode	Optical Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type	
980=980nm	01=1/99	P=Same Fiber	1=1x2	B=B Type	1=1W	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N=Without Connector	
	05=5/95	S=Corr. SM Fiber	2=2x2	Blank for Standard	2=2W	Blank for SST	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector	
	10=10/90	5=50/125um Fiber			5=5W	or >10W	Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector	
	50=50/50				10=10W		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector	