

1053nm 4-port High Power Optical Circulator

FEATURES

- High Isolation 0
- **ÅPPLICATIONS** Fiber Optic Amplifiers

0

0

- Low Insertion Loss
- 0
- **Epoxy-Free Optical Path** 0 High Reliability and Stability 0
- **Dispersion Compensation** 0

WDM Systems

Fiber Optic Instruments

- Low Profile Packaging 0
- Light Routing 0

SPECIFICATIONS

Parameter		Unit	Value		
Center Wavelength		nm	1053		
Operating Wavelength Range		nm	+/-10		
Insertion Loss@ 23 °C	(Typ.)	dB	0.9		
Insertion Loss@ 25 °C	(Max.)	dB	1.5		
	С Туре	-	1→2, 2→3, 3→4 (Loss:4→1 is Uncontrolled)		
Optical Path	D Type	-	1→2, 2→3, 3→4, 4→1		
	Е Туре	-	1 → 2, 2 → 3, 3 → 4 (4 → 1 is Isolated)		
Isolation @ 23 °C	(Typ.)	dB	23		
	(Min.)	dB	20		
Optical Return Loss		dB	≥45		
Polarization Dependent Loss		dB	≤0.2		
			HI1060 Fiber or 10/125um SC Fiber (E)		
Fiber Type		-	10/125um DC Fiber (0), 15/130um DC Fiber (W)		
			20/130um DC Fiber (Q) or 25/250um DC Fiber (R)		
Fiber Tensile Load		N	5		
Maximum Total Optical Power (CW)		W	0.5, 1, 2, 3, 5, 10, 15, 20, 25, 30		
Operating Temperature		°C	0~50		
Storage Temperature		°C	-20~75		

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.5dB higher, RL is 5dB lower.

3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.


4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

32

25

5. Package size may be different for different optical power, configuration and fiber types.

DIMENSION DRAWING



ORDERING INFORMATION (PN)

FCIR- NNNN	- (<mark>C</mark>)	-4HP NN	- (NN/NN)	- (<mark>NN</mark>)	- (<mark>C</mark>)	С	NN	-CC/CCC
Center Wavelength	Optical Path	Optical Power(Total)	Optical Power P2/P3	Optical Power P4	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1053-1053nm	D=D Type	<mark>05</mark> –500mW	<mark>1-</mark> 1W	<mark>1</mark> - 1W	E=10/125 SC Fiber	<mark>B=</mark> Bare fiber	<mark>05</mark> =0.5m	N–Without Connector
	E=E Type	1-1W	<mark>2</mark> = 2W	<mark>2</mark> = 2W	Q= 20/130 DC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	<i>Blank</i> for C Type	<mark>5=</mark> 5W	<mark>5</mark> =5W	<mark>5</mark> =5W	R=25/250 DC Fiber	<mark>2</mark> = 2mm Cable	<mark>15</mark> =1.5m	LC/PC=LC/PC Connector
		<mark>20</mark> -20W	<i>Blank</i> for P2/3=P1	<i>Blank</i> for None	<i>Blank</i> for H11060 Fiber	<mark>3=</mark> 3mm Cable	<mark>20</mark> =2.0m	SC/UPC=SC/UPC Connector

